

A close-up photograph of a speaker driver, showing the central tweeter and surrounding horn structure. The image is overlaid with a semi-transparent red gradient that is darker at the top and lighter towards the bottom. The text 'ACR' is prominently displayed in the center in a large, white, bold, sans-serif font.

ACR

moving ahead to the future of sound

PCT 2500 ACR

Ukuran	: 1 Inch
Daya Maksimum ¹	: 200 Watt
Sensitivity	: 105 dB
Material	: Plastik

(¹) IEC 268-5, (in box system, cut.off 20-500 Hz)



PCT 6100 ACR

Ukuran	: 1 Inch
Daya Maksimum ¹	: 75 Watt
Sensitivity	: 94 dB
Material	: Plastik

(¹) IEC 268-5, (in box system, cut.off 20-500 Hz)



PCT 410 ACR

Ukuran	: 1 Inch
Daya Maksimum ¹	: 300 Watt
Sensitivity	: 105 dB
Material	: Plastik

(¹) IEC 268-5, (in box system, cut.off 20-500 Hz)



PCT 155 ACR

Ukuran	: 1 Inch
Daya Maksimum ¹	: 300 Watt
Sensitivity	: 105 dB
Material	: Plastik

(¹) IEC 268-5, (in box system, cut.off 20-500 Hz)



AX 155 ACR

1 inch Dome Tweeter Horn - ACR

Diameter Throat	: 1 Inch
Ukuran	: 5 x 15 Inch
Impedansi	: 8 Ohm
Daya Maksimum ¹	: 250 Watt
Lebar Daerah Frekuensi	: 2 kHz - 16.1 KHz
Sensitivity	: 93 dB
Diameter Voice Coil	: 25.4 mm / 1 inch
Material Voice Coil	: Newcon
Tipe Pemasangan	: Screw-On



AX 975 HT ACR

1 inch Dome Tweeter Horn - ACR

Diameter Throat	: 1 Inch
Ukuran	: 4.3 x 10.5 Inch
Impedansi	: 8 Ohm
Daya Maksimum ¹	: 250 Watt
Lebar Daerah Frekuensi	: 1.7 kHz - 20 KHz
Sensitivity	: 105 dB
Diameter Voice Coil	: 25.4 mm / 1 inch
Material Voice Coil	: Newcon
Tipe Pemasangan	: Screw-On



HORN H-225 ACR

Diameter Throat	: 1 Inch
Ukuran	: 225 x 225 mm
Material	: Plastik



CD 250C1-08F (CD 1-Mk1)

1 inch Tweeter - ACR

Diameter Throat	: 1 Inch
Impedansi	: 8 Ohm
Nominal Power Handling ¹	: 20 W
Program Power ²	: 40 W
Lebar Daerah Frekuensi	: 3 KHz - 20 KHz
Sensitivity	: 97 dB
Diameter Voice Coil	: 25.4 mm / 1 inch
Diaphragm Material	: Cloth
Medan Magnet	: 1.45 T
Material Magnet	: Ferrite
Tipe Pemasangan	: Screw-On



RECONE KIT AVAILABLE

CD 250T1-08F (CD 2-Mk1)

1 inch Tweeter - ACR

Diameter Throat	: 1 Inch
Impedansi	: 8 Ohm
Nominal Power Handling ¹	: 20 Watt
Program Power ²	: 40 Watt
Lebar Daerah Frekuensi	: 2.5 KHz - 20 KHz
Sensitivity	: 99 dB
Diameter Voice Coil	: 25.4 mm / 1 inch
Diaphragm Material	: Titanium
Medan Magnet	: 1.6 T
Material Magnet	: Ferrite
Tipe Pemasangan	: Screw-On



RECONE KIT AVAILABLE

CD 380C1-08 (CD 6)

1 inch Tweeter - ACR

Diameter Throat	: 1 Inch
Impedansi	: 8 Ohm
Nominal Power Handling ¹	: 20 Watt
Program Power ²	: 40 Watt
Lebar Daerah Frekuensi	: 2 KHz - 18 KHz
Sensitivity	: 96 dB
Diameter Voice Coil	: 37.4 mm / 1.5 inch
Diaphragm Material	: Cotton-CT
Medan Magnet	: 1.6 T
Material Magnet	: Ferrite
Tipe Pemasangan	: Screw-On



RECONE KIT AVAILABLE

CD 340T1B-08F (CD 9B-Mk1)

1 inch Tweeter - ACR

Diameter Throat	: 1 Inch
Impedansi	: 8 Ohm
Nominal Power Handling ¹	: 30 Watt
Program Power ²	: 60 Watt
Lebar Daerah Frekuensi	: 1.5 KHz - 20 KHz
Sensitivity	: 98 dB
Diameter Voice Coil	: 34.4 mm / 1.3 inch
Diaphragm Material	: Titanium
Medan Magnet	: 1.5 T
Material Magnet	: Ferrite
Tipe Pemasangan	: Bolt-On



RECONE KIT AVAILABLE

CD 250P1-08 (CD 10)

1 inch Tweeter - ACR

Diameter Throat	: 1 Inch
Impedansi	: 8 Ohm
Nominal Power Handling ¹	: 20 W
Program Power ²	: 40 W
Lebar Daerah Frekuensi	: 2 KHz - 20 KHz
Sensitivity	: 101 dB
Diameter Voice Coil	: 25.4 mm / 1 inch
Diaphragm Material	: Polyetherimide
Medan Magnet	: 1.7 T
Material Magnet	: Ferrite
Tipe Pemasangan	: Screw-On



RECONE KIT AVAILABLE

8" C 810 DFH

8 inch Woofer - ACR

Diameter Speaker	: 8 inch / 203.2 mm
Impedansi	: 8 Ω
Nominal Power Handling ²	: 30 Watt
Program Power ³	: 60 Watt
Lebar Daerah Frekuensi	: 58 Hz - 8.6 KHz
Sensitivity	: 92 dB
Diameter Cone Efektif	: 165 mm
Medan Magnet	: 1.16 T
Berat Magnet	: 0.36 kg /12.7 Oz
Material Magnet	: Ferrite
Diameter Voice Coil	: 25.4 mm / 1 inch
Material Voice Coil	: Kraft



10" C-1018 HW

10 inch Fullrange - ACR Pro New

Diameter Speaker	: 10 inch / 254 mm
Impedansi	: 8 Ω
Daya Maksimum ¹	: 300 Watt
Lebar Daerah Frekuensi	: 57 Hz - 15.7 KHz
Sensitivity	: 93 dB
Diameter Cone Efektif	: 210 mm
Medan Magnet	: 0.87 T
Berat Magnet	: 0.48 kg / 16.9 Oz
Material Magnet	: Ferrite
Diameter Voice Coil	: 36 mm / 1.4 inch
Material Voice Coil	: ASV



12" 1238 PC CLASSIC

12 inch Fullrange - ACR Classic New

Diameter Speaker	: 12 inch / 305 mm
Impedansi	: 8 Ω
Daya Maksimum ¹	: 500 Watt
Lebar Daerah Frekuensi	: 41 Hz - 16.8 KHz
Sensitivity	: 95 dB
Diameter Cone Efektif	: 254 mm
Medan Magnet	: 0.94 T
Berat Magnet	: 0.81 kg / 28.5 Oz
Material Magnet	: Ferrite
Diameter Voice Coil	: 36 mm / 1.4 inch
Material Voice Coil	: Kapton



VOICE COIL AVAILABLE

12" 1240-Mk1 PA CLASSIC

12 inch Fullrange - ACR Classic

Diameter Speaker	: 12 inch / 305 mm
Impedansi	: 8 Ω
Nominal Power Handling ²	: 80 Watt
Program Power ³	: 160 Watt
Lebar Daerah Frekuensi	: 33 Hz - 13.6 KHz
Sensitivity	: 99 dB
Diameter Cone Efektif	: 251 mm
Medan Magnet	: 1.26 T
Berat Magnet	: 1.31 kg / 46.0 Oz
Material Magnet	: Ferrite
Diameter Voice Coil	: 45.5 mm
Material Voice Coil	: Kapton



VOICE COIL AVAILABLE

12" 1225 NEW

12 inch Fullrange - ACR New

Diameter Speaker	: 12 inch / 305 mm
Impedansi	: 8 Ω
Nominal Power Handling ²	: 100 Watt
Program Power ³	: 200 Watt
Lebar Daerah Frekuensi	: 52 Hz - 10.6 KHz
Sensitivity	: 96 dB
Diameter Cone Efektif	: 260.5 mm
Medan Magnet	: 1.23 T
Berat Magnet	: 0.81kg / 28.5 Oz
Material Magnet	: Ferrite
Diameter Voice Coil	: 36 mm / 1.4 inch
Material Voice Coil	: ASV



VOICE COIL AVAILABLE

12" 1230 BLACK

12 inch Fullrange - ACR Black

Diameter Speaker	: 12 inch / 305 mm
Impedansi	: 8 Ω
Nominal Power Handling ²	: 100 Watt
Program Power ³	: 200 Watt
Lebar Daerah Frekuensi	: 50 Hz - 16.8 kHz
Sensitivity	: 97 dB
Diameter Cone Efektif	: 260.5 mm
Medan Magnet	: 1.03 T
Berat Magnet	: 1.0 kg / 35.08 Oz
Material Magnet	: Ferrite
Diameter Voice Coil	: 38.5 mm / 1,5 inch
Material Voice Coil	: Tilt



VOICE COIL AVAILABLE

15" 15200 NEW

15 inch Woofer - ACR New

Diameter Speaker	: 15 inch / 381 mm
Impedansi	: 8 Ω
Daya Maksimum ¹	: 350 Watt
Lebar Daerah Frekuensi	: 33 Hz - 4.5 KHz
Sensitivity	: 97 dB
Diameter Cone Efektif	: 332 mm
Medan Magnet	: 1.1 T
Berat Magnet	: 1.16 kg / 40.6 Oz
Material Magnet	: Ferrite
Diameter Voice Coil	: 49.5 mm / 1.9 inch
Material Voice Coil	: Asv



VOICE COIL AVAILABLE

15" 15500 BLACK

15 inch Fullrange - ACR Black Platinum

Diameter Speaker	: 15 inch / 381 mm
Impedansi	: 8 Ω
Nominal Power Handling ²	: 200 Watt
Program Power ³	: 400 Watt
Lebar Daerah Frekuensi	: 45 Hz - 4 KHz
Sensitivity	: 98 dB
Diameter Cone Efektif	: 332 mm
Medan Magnet	: 1.15 T
Berat Magnet	: 1.83 kg / 64.1 Oz
Material Magnet	: Ferrite
Diameter Voice Coil	: 60.5 mm / 2.4 inch
Material Voice Coil	: Till



VOICE COIL AVAILABLE

15" 15600+ BLACK

15 inch Woofer - ACR Black

Diameter Speaker	: 15 inch / 381 mm
Impedansi	: 8 Ω
Nominal Power Handling ²	: 250 Watt
Program Power ³	: 500 Watt
Lebar Daerah Frekuensi	: 42 Hz - 3.85 KHz
Sensitivity	: 98 dB
Diameter Cone Efektif	: 324 mm
Medan Magnet	: 1.18 T
Berat Magnet	: 1.83 kg / 64.1 Oz
Material Magnet	: Ferrite
Diameter Voice Coil	: 60.5 mm
Material Voice Coil	: Till



15" 15600 BLACK

15 inch Woofer - ACR Black

Diameter Speaker	: 15 inch / 381 mm
Impedansi	: 8 Ω
Daya Maksimum ¹	: 500 Watt
Lebar Daerah Frekuensi	: 42 Hz - 4.2 KHz
Sensitivity	: 98 dB
Diameter Cone Efektif	: 324 mm
Medan Magnet	: 1.1 T
Berat Magnet	: 1.83 kg / 64 Oz
Material Magnet	: Ferrite
Diameter Voice Coil	: 60.5 mm / 2.4 inch
Material Voice Coil	: Tilt



VOICE COIL AVAILABLE

21" AX 21800 MK1

21 inch Subwoofer - ACR Black Grand

Diameter Speaker	: 21 inch / 533.4 mm
Impedansi	: 8 Ω
Nominal Power Handling ²	: 500 Watt
Program Power ³	: 1000 Watt
Lebar Daerah Frekuensi	: 25 Hz - 2820 Hz
SPL	: 99.5 dB
Diameter Cone Efektif	: 494 mm
Medan Magnet	: 1.08 T
Berat Magnet	: 3.4 kg / 119.7 Oz
Material Magnet	: Ferrite
Diameter Voice Coil	: 99.2 mm / 3.9 inch
Material Voice Coil	: Tilt



VOICE COIL AVAILABLE



Notes :

(¹) IEC 268-5, (in box system, cut.off 20-500 Hz)

(²) AES standard, test mode with continuous pink noise signal (6 dB crest factor; 2 hours) within the F_0 to $10F_0$ power calculated on rated nominal impedance. Loudspeaker in free air

(³) Power on continous program is defined as 3dB greater than nominal power handling.

MORE INFORMATION

Showroom Surabaya

Jl. Genteng Besar No.43, Surabaya
(Genteng Electronic Center, Lt.2 No.201-203)
Telp. +62 8123 1833 504 , +62 8121 7334 084

Showroon Jakarta

Ruko Glodok Plaza Blok F, No. 97,
Mangga Besar - Jakarta Barat
Telp. +62 21 649 3139 / +62 21 649 3171

www.acrspeaker.com

 **ACR SPEAKER**

 **ACRSPEAKER**

 **ACR - RHYME PRO AUDIO**

100%
INDONESIA

www.acrspeaker.com

